

## 5. BASIC OPERATIONS

d. When the call is ended, it will display "Call end", and you can press [PTT] to respond the call.

### 5.10 Making a Call

**Method 1:** from the Channel switch.

Turn the channel switch to choose a programmed channel.

**Method 2:** from the Talk Group.

(1) Turn the channel switch to choose a programmed channel;

(2) Press  (exit) key to enter the TG List, press the  /  key to choose a TG.

**Method 3:** from the keypad.

(1) Turn the channel switch to choose a programmed channel.

(2) Press  (Menu) key to Talk Group, press select to enter TG.

(3) Press  /  key to Manual Dial, press Select.

(4) Input the ID number by keypad, press  key to switch group ID or Private DMR ID.

Hold the radio vertical 2.5-5cm from your mouth, press the [PTT] key to start the call, the red LED lights up, the receiver ID/name/city/state/country/call type and call out icon will be display on the LCD.

Release [PTT] key to receive the reply.

### 5.11 Monitor

In standby, press the [PF2] key to enter Monitor. When receiving matched carrier but the signaling / ID is unmatched or the signal is too weak, this function allows monitor the weak signal and signal with unmatched ID.

Press the [PF2] key again to shut off speaker and return to standby.

 » **When in analog mode, if no signal, it will emit noise when press the Monitor Key.** \*\* The Rx icon is seen when monitor is activated.

NOTE

### 5.12 Emergency Alarm

Press Emergency Alarm key [PF3] to turn alarm function, then press this key again to return.

### 5.13 Man Down Alarm

a. Press  (Menu) to enter main Menu, press  /  key to Settings.

b. Select Radio Set, press, press  /  key to Man Down.

c. Select Man Down On to turn on the function.